



Product number GWP-SF-RZRWT:

GWP-SF-RZRWT uses FRS (Family Radio Service) frequencies for 2-way communication. The Family Radio Service (FRS) is a private, two-way, short-distance voice and data communications service for facilitating family and group activities. The most common use for FRS channels is short-distance, two-way voice communications using small hand-held radios that are similar to walkie-talkies.

FRS is licensed by rule. This means an individual license is not required to operate an FRS radio provided you comply with the rules. You may operate an FRS radio regardless of your age, and for personal or for business use if you are not a representative of a foreign government

The FRS is authorized 22 channels in the 462 MHz and 467 MHz range, all of which are shared with GMRS (General Mobile Radio Service). There are 22 FRS channels. Each channel has a bandwidth of 12.5 kHz, but the power of each channel may vary as indicated below.

Channel No.	Frequency	Power (ERP in Watts)
1	462.5625	2 W
2	462.5875	2 W
3	462.6125	2 W
4	462.6375	2 W
5	462.6625	2 W
6	462.6875	2 W
7	462.7125	2 W
8	467.5625	0.5 W
9	467.5875	0.5 W
10	467.6125	0.5 W
11	467.6375	0.5 W
12	467.6625	0.5 W
13	467.6875	0.5 W
14	467.7125	0.5 W
15	462.55	2 W
16	462.575	2 W
17	462.6	2 W
18	462.625	2 W
19	462.65	2 W
20	462.675	2 W
21	462.7	2 W
22	462.725	2 W